

Martindale Tester Kit with ET4 C/W MP21-08 Leads And Case

Product Images

Product Code: C72-7370



Short Description

The ET4 is a very compact electrical tester that measures AC/DC voltage, resistance and AC/DC current.

Continuity with a buzzer is also included.

It can also measure frequency and continuity and will take simultaneous measurement of current/voltage and frequency / voltage by employing the open jaw clamp and test probes simultaneously.

This electrical tester can be used as a non-contact voltage indicator using the inbuilt sensor in the left tip of the open jaw clamp and has auto-ranging, display hold and auto power-off functions.

The right tip of the jaw has a forward-facing LED light to illuminate the local working area.

The ET4 is supplied with **Drummond MP21-08 CAT IV Rated Fused Lead Set**, a soft carry case with belt loop, 9V battery and manual.

Features

- AC/DC voltage up to 600V
- AC/DC Current up to 200A
- Continuity (with buzzer < 30 Ω)
- Frequency measurement 30Hz- 400Hz
- Carry case with belt loop

Specifications

Current AC: 0.1A-200.0A, Accuracy: $\pm(2.0\%$ of rdg + 10 dgt)

DC: 0.1A-200.0A, Accuracy: $\pm (2.0\%$ of rdg + 5 dgt)

Voltage AC: 0.1mV-600V, Accuracy: $\pm (1.2\%$ of rdg + 5 dgt)

DC: 0.1mV-600V, Accuracy: $\pm (0.5\%$ of rdg + 2 dgt)

Resistance 0.1 Ω -50M Ω , $\pm (1\%$ of rdg + 5 dgt)

Frequency 30Hz-400Hz, $\pm (0.1\%$ of rdg + 5 dgt)

Continuity Buzzer at<30 Ω

Diode Test 1mV-2V

NCV indicator 70V- 600V

Supply 9V PP3 Alkaline

Weight 200g (incl battery)

Dimensions 202 x 51 x 44 mm

Includes Drummond MP21-08 CAT IV Rated Fused Lead Set, 9V battery, case and manual

Description

The ET4 is a very compact electrical tester that measures AC/DC voltage, resistance and AC/DC current. Continuity with a buzzer is also included.

It can also measure frequency and continuity and will take simultaneous measurement of current/voltage and frequency / voltage by employing the open jaw clamp and test probes simultaneously.

This electrical tester can be used as a non-contact voltage indicator using the inbuilt sensor in the left tip of the open jaw clamp and has auto-ranging, display hold and auto power-off functions.

The right tip of the jaw has a forward-facing LED light to illuminate the local working area.

The ET4 is supplied with **Drummond MP21-08 CAT IV Rated Fused Lead Set**, a soft carry case with belt loop, 9V battery and manual.

Features

AC/DC voltage up to 600V

AC/DC Current up to 200A

Continuity (with buzzer < 30 Ω)

Frequency measurement 30Hz- 400Hz

Carry case with belt loop

Specifications

Current AC: 0.1A-200.0A, Accuracy: $\pm(2.0\%$ of rdg + 10 dgt)

DC: 0.1A-200.0A, Accuracy: $\pm(2.0\%$ of rdg + 5 dgt)

Voltage AC: 0.1mV-600V, Accuracy: $\pm(1.2\%$ of rdg + 5 dgt)

DC: 0.1mV-600V, Accuracy: $\pm(0.5\%$ of rdg + 2 dgt)

Resistance 0.1 Ω -50M Ω , $\pm(1\%$ of rdg + 5 dgt)

Frequency 30Hz-400Hz, $\pm(0.1\%$ of rdg + 5 dgt)

Continuity Buzzer at <30 Ω

Diode Test 1mV-2V

NCV indicator 70V- 600V

Supply 9V PP3 Alkaline

Weight 200g (incl battery)

Dimensions 202 x 51 x 44 mm

Includes Drummond MP21-08 CAT IV Rated Fused Lead Set, 9V battery, case and manual